

VCS 500N10

COMBINATION WAVE SIMULATOR



FOR TESTS ACCORDING TO ...

- › EN 61000-4-5
- › EN 61000-4-9
- › IEC 60255-22-5
- › IEC 61000-4-5
- › IEC 61000-4-9
- › IEC 61326
- › IEC 61850-3
- › ITU-T K.12
- › ITU-T K.20
- › ITU-T K.45

COMBINATION WAVE SIMULATOR







Surge pulses occur due to direct or indirect lightning strokes to an external (outdoor) circuit. This leads to currents or electromagnetic fields causing high voltage or current transients. Another source for surge pulses are switching transients originating from switching disturbances and systems faults.

Due to the characteristic of the phenomenon nearly every electrical and electronic device may suffer from such lightning events which justifies the necessity of surge tests being widely performed. Surge voltage can reach several thousands of volts and surge current is seen to reach several thousands of amps.

HIGHLIGHTS

- › Surge pulses up to 10kV/5kA
- › Single phase or three-phase coupler up to 100A (external options)
- › Fail inputs
- › Warning lamp control
- › Emergency interlock
- › Standard test routines

APPLICATION AREAS

- | | |
|--|---|
|  INDUSTRY |  TELECOM |
|  COMPONENTS |  RESIDENTIAL |
|  MEDICAL | |
|  BROADCAST | |

TECHNICAL DETAILS

COMBINATION WAVE 1.2/50US - 8/20US

Voltage (o.c.)	500V - 10,000V ± 10%
Pulse front time	1.2us ± 30%
Pulse time to half value	50us ± 20%
Current (s.c.)	max. 5,000A ± 10%
Pulse front time	8us ± 20%
Pulse time to half value	20us ± 20%
Polarity	Positive/negative/alternating
Event counter	1 - 30,000 or endless

TRIGGER

Trigger of events	Automatic, manual, extern
CRO trigger	5V trigger signal for oscilloscope
Synchronization	0° - 360°, resolution 1°
Repetition rate	6s - 999s, depending on the voltage

OUTPUT

Direct	2 outputs via HV connectors; - Zi = 2ohm - for external coupling networks
--------	---

MEASUREMENTS

CRO Ū-monitor	10Vp at 10,000V
CRO Î-monitor	10Vp at 5,000A
Peak voltage	10,000V in the LCD display
Peak current	5,000A in the LCD display

TEST ROUTINES

Quick Start	Immediate start, easy-to-use and fast
User Test routines	Change Polarity after n pulses Change voltage after n pulses
Standard Test routines	As per IEC 61000-4-5, Level 1,000V As per IEC 61000-4-5, Level 2,000V As per IEC 61000-4-5, Level 4,000V Manual Standard Test routine
Service	Service, setup, self test

INTERFACE

Serial interface	USB
Parallel interface	IEEE 488, addresses 1 - 30
CN interface	To control external coupling matrix

SAFETY

Safety circuit	Control input (24Vdc)
Warning lamp	Floating output contact

GENERAL DATA

Dimensions, weight	19"/6HU, approx. 35kg
Supply voltage	115/230V +10/-15%
Fuses	2 x T 2AT (230V) or 2 x T4AT (115V)

COUPLING/DECOUPLING NETWORKS FOR POWER LINES

CNI 503A16	3phase coupling/decoupling network for EFT and Surge; 3x440V/16A
CNI 503A18	3phase coupling/decoupling network for EFT and Surge; 3x440V/32A
CNI 503A19	3phase coupling/decoupling network for EFT and Surge; 3x440V/63A
CNI 503A20	3phase coupling/decoupling network for EFT and Surge; 3x440V/100A
CNV 501S4	1phase coupling/decoupling network for Surge; 250V/16A
CNV 503S9	3phase coupling/decoupling network for Surge; 3x440V/16A
CNV 503S10	3phase coupling/decoupling network for Surge; 3x440V/32A
CNV 503S11	3phase coupling/decoupling network for Surge; 3x440V/63A
CNV 503S12	3phase coupling/decoupling network for Surge; 3x440V/100A

COUPLING/DECOUPLING NETWORKS FOR SIGNAL/TELECOM LINES

CNV 504Nx	4 signal lines as per fig. 11 & 12, IEC 61000-4-5
CNV 504S1	4 telecom lines as per fig. 14, IEC 61000-4-5
CNV 508Nx	8 signal lines as per fig. 11 & 12, IEC 61000-4-5
CNV 508S1	8 telecom lines as per fig. 14, IEC 61000-4-5

PULSED MAGNETIC FIELD AS PER IEC 61000-4-9

MS 100N	Magnetic field coil for up to 3,200A/m
---------	--

COMPETENCE WHEREVER YOU ARE



CONTACT EM TEST DIRECTLY

Switzerland

EM TEST (Switzerland) GmbH › Sternenhofstraße 15 › 4153 Reinach › Switzerland
Phone +41 (0)61/7179191 › Fax +41 (0)61/7179199
Internet: www.emtest.ch › E-mail: sales.emtest@ametek.com

Germany

EM TEST GmbH › Lünener Straße 211 › 59174 Kamen › Deutschland
Phone +49 (0)2307/26070-0 › Fax +49 (0)2307/17050
Internet: www.emtest.com › E-mail: info.emtest@ametek.de

France

EM TEST FRANCE › Le Trident - Parc des Collines › Immeuble B1 - Etage 3 › 36, rue Paul Cézanne › 68200 Mulhouse › France
Phone +33 (0)389 31 23 50 › Fax +33 (0)389 31 23 55
Internet: www.emtest.fr › E-mail: info@emtest.fr

Poland

EM TEST Polska › ul. Ogrodowa 31/35, 00-893 Warszawa › Polska
Phone +48 (0)518 64 35 12
Internet: www.emtest.com/pl › E-mail: info_polska.emtest@ametek.de

USA / Canada

EM TEST USA › 9250 Brown Deer Road › San Diego › CA 92121
Phone +1 (858) 699 1685 › Fax +1 (858) 458 0267
Internet: www.emtest.com › E-mail: sales.emtest@ametek.com

P.R. China

E & S Test Technology Limited › Rm 913, Leftbank › No. 68 Bei Si Huan Xi Lu › Haidian District › Beijing 100080 › P.R. China
Phone +86 (0)10 82 67 60 27 › Fax +86 (0)10 82 67 62 38
Internet: www.emtest.com › E-mail: info@emtest.com.cn

Republic of Korea

EM TEST Korea Limited › #405 › WooYeon Plaza › #986-8 › YoungDeok-dong › Giheung-gu › Yongin-si › Gyeonggi-do › Korea
Phone +82 (31) 216 8616 › Fax +82 (31) 216 8616
Internet: www.emtest.co.kr › E-mail: sales@emtest.co.kr

Information about scope of delivery, visual design and technical data correspond with the state of development at time of release. Technical data subject to change without further notice.