


*EMC Antennas*  
**Double-Ridged  
Waveguide Horn  
with Pre-Amplifier**

Model 3117-PA

**FEATURES:**

- 1 GHz to 18 GHz Frequency Range
- Maintains Single Lobe Radiation
- Fitted with Pre-Amplifier for Increased Sensitivity
- Extremely Low Antenna Factor
- Flexible Mounting



*ETS-Lindgren's Model 3117-PA Double-Ridged Waveguide Horn Antenna with Pre-Amplifier*

**ETS-LINDGREN'S MODEL 3117-PA** is a special version of our popular Model 3117 Double-Ridged Waveguide Horn Antenna, fitted with a pre-amplifier package and calibrated as a single unit. By doing this, any possible mismatches between antenna and pre-amplifier are taken into account in the antenna factor (AF), which is provided with this unit. The antenna is ideal as a receive antenna for emissions testing above 1 GHz.

**FEATURES**

**Frequency Range**

This antenna covers the 1 GHz to 18 GHz range making it ideal as a receive antenna for any emissions testing above 1 GHz.

**Maintains Single Lobe Radiation**

Like the Model 3117, the Model 3117-PA maintains a single main lobe pattern in the direction of the horn axis over its frequency range. This characteristic is essential for even distribution of electromagnetic

energy on a target surface, and accurate measurement of gain and emissions. The model 3117's unique design suppresses the propagation of high order modes. The result is an antenna with a well-defined single lobe radiation pattern that outperforms other antennas in its class.

**Fitted Amplifier**

The pre-amplifier attached to the antenna has a frequency range of 1 GHz to 18 GHz and a typical gain of 48 dB. The gain flatness across the range is  $\pm 2.5$  dB. The pre-amplifier has a maximum noise figure of 4 dB maximum with the typical noise figure being 3 dB. The power output is +17 dB minimum at the 1 dB point. The input and output characteristics of the preamplifier are an Input and output VSWR of 2:1 maximum.

**Low Antenna Factor**

The result of matching the Model 3117 with the pre-amplifier is an antenna that is calibrated as a

system and it provides an extremely low AF that is less than -2 dB (1/m) for the entire frequency range.

**Flexible Mounting**

The Model 3117-PA includes both a 1/4 20 thread classic mount and a rear "stinger" mount.

**STANDARD CONFIGURATION**

- Antenna and Pre-amplifier
- Mounting Bracket for 1/4 20 Threads
- Stinger Mount
- AC/DC Power Supply for the Pre-amplifier Module
- Individually Calibrated Factors at 1m and 3m per SAE ARP 958
- Manual

**OPTIONS**

- 4-TR Tripod
- 7-TR Tripod

## Electrical Specifications

MODEL	FREQUENCY RANGE	VSWR (AVG)	MAXIMUM CONTINUOUS POWER	IMPEDANCE (NOMINAL)	CONNECTOR TYPE
3117-PA	1 GHz to 18 GHz	N/A (Rx Only)	N/A (Rx Only)	50 Ω	SMA (Female)

## Physical Specifications

MODEL	LENGTH*	WIDTH	HEIGHT*	WEIGHT
3117-PA	33.0 cm 13.0 in	17.5 cm 6.9 in	19.7 cm 7.8 in	1.4 kg 3.0 lb

\*Includes stinger and pre-amplifier box.

## Model 3117-PA Typical Antenna Factor and Gain

